




DIP SWITCH DETAIL



DIP SWITCH LEGEND

DEFAULT SETTINGS



The Micro Comm driver must be programmed to send messages with the level required to activate the features listed below. Level 0 messages will always be displayed, regardless of DIP switch or resistor settings.

For message blocking, turn on DIP switch 1 (MB). This will block level 1 and level 3 messages from being displayed.

To blank the display during a fire main (level three) message, turn on DIP switch 2 (FM).

To blank the display during a fire alternate (level two) message, remove resistor R20 (FA) from the board.

To operate this display as a rear unit remove resistor R8 (R) from the board.

NOTE: The Micro Comm driver must be sending the MC2000 data stream to use this feature. Call Tech Support at 419-636-6705 for more information.

NOTE: MUST BE USED WITH A CLASS 2 POWER SUPPLY.

CODE VERSION _____

BOARD VERSION CE2852 _____

DATE DRAWN: 01/03/06	DRAWN BY: DAC	REQUESTED BY: DC	C.E. ELECTRONICS, INC. 2107 Industrial Drive Bryan, Ohio 43006 (419) 636-6705
BOARD NUMBER: 2852	LAST DATE REVISED: -	APPROVED BY:	
PRODUCT: VF212 MC VF DISPLAY ON OTIS SQ FOOTPRINT			
			DWG. NO. VF212_01
			REV. -